



Quick Start Guide

EXISTING ACCOUNT INSTRUCTIONS UUPlus Personal

Each satellite phone UUPlus supports requires a different modem init string. Select the appropriate modem during the configuration process.

High Bandwidth IP:	+UUPlus UMTF Secure Mail Transport //only for very fast connections
Mid to Low Bandwidth IP:	+UUPlus VPN Secure IP Connection //use for most IP connections
Iridium (Land line No.):	+Iridium Satellite Phone
Iridium (Iridium No.):	+Iridium to Iridium Call
Mini-M:	+Nera Saturn - WorldPhone - World Communicator +9600 baud Generic Mini-M Phone +2400 baud Mini-M Phone (older)
Inmarsat (not MPDS):	+Fleet 33-55-77
Inmarsat B:	+Inmarsat B Satellite Phone
Globalstar:	+Globalstar GSP-1600 Satellite Phone +Globalstar GSP-2900 Satellite Phone
Thuraya:	+Thuraya Satellite Phone
ACeS:	+ACeS Satellite Phone
Motient:	+Mitsubishi 4800 Baud St-Series Phone +Mitsubishi 2400 Baud St-Series Phone
Optus Sat:	+NEC S2 Satellite Phone

If you are installing over an existing installation, be sure to exit all UUPlus programs before beginning the installation.

1. Place the UUPlus CD in the CD-ROM or run Personal.exe, which can be downloaded from the UUPlus web site <www.uuplus.com>.
2. From the UUPlus Installation Window, select [**UUPlus Personal**].
3. Carefully read the 'Welcome to UUPlus Setup' page and click [**Next**].
4. Carefully read the 'UUPlus Software License Agreement' and click [**Accept**]. You must accept the License Agreement to continue with the installation.
5. Carefully read the 'UUPlus Personal/Personal Pro' readme file for any new information or installation tips and click [**Next**].
6. The software will want to install to the path "C:\UUPlus". UUPlus software cannot be installed into folders containing a space in their path. Click [**OK**].
7. Click [**Next**] to copy the UUPlus software onto your hard disk.
8. After software has successfully copied itself, Personal will launch automatically.
9. A dialog box will appear informing you of your account options. Click [**OK**].
10. Select [**Existing**] to configure Personal with your existing account.
11. Enter your User Name and Password in the appropriate fields and click [**OK**].
12. On the [**Modems**] tab, the Available Modems list displays all the UUPlus modems, all the VPN modes for any Windows Dial-up Networking account configured on this computer as well as any Windows install modems. The UUPlus modems are indicated with a "+" symbol. If you are using a satellite phone UUPlus recommends you first try a UUPlus modem. Select the appropriate modem for your sat phone and click [Add].
13. On the [**Modem Settings**] tab select the appropriate COM Port and click [**Done Editing Modem**].
14. Leave everything as default on the [**Calling**] tab and click [**Next**]. You can make changes to the calling parameters later on.
15. Click [**OK**] for the dialog box explaining how to configure your POP compatible mailer.
16. Click [**OK**] for the dialog box explaining how to access the pop up help and user guide.
17. UUPlus Personal is now configured and ready for use.

If you experienced problems calling over your satellite phone, please refer to the modem configuration help files or contact UUPlus support.