



Quick Start Guide

NEW SITE INSTRUCTIONS UUPlus SOHO

Each satellite phone UUPlus supports requires a different modem init string. Select the appropriate modem during the configuration process.

ACeS:	+ACeS Satellite Phone
Iridium:	+Iridium Satellite Phone
Globalstar:	+Globalstar GSP-1600 Satellite Phone
Mini-M:	+9600 baud Mini-M Satellite Phone or +2400 baud Mini-M Satellite Phone
Motient:	+Mitsubishi 4800 Baud ST-Series Phone or +Mitsubishi 2400 Baud ST-Series Phone
Thuraya:	+Thuraya Satellite Phone

For Cell Phones, use the driver that came with your cell phone's data kit or +14400 baud Cell Phone in the [Available Modems] list.

Place the UUPlus CD in the CD-ROM or run SOHO.exe, which is available from the website.

1. Select UUPlus SOHO and proceed through the installation process. After installation, SOHO will automatically run and place a shortcut on your desktop.
2. On startup for the first time, SOHO will display a window informing you of your account setup options.
3. Click [**OK**] and then select [**UUPlus**] to configure the multi-user account.
4. Enter your UUPlus multi-user satellite email account name. Please contact UUPlus to obtain an account. A SOHO account cannot be created remotely like a UUPlus Personal account can. Click [**OK**] to continue.
5. Enter the name of your UUPlus account password. This will also be used as your postmaster's password. All unroutable mail will be routed to the postmaster mailbox. The postmaster mailbox does not need to be called postmaster. Click [**OK**] to continue.
6. Select [**Yes**] if you want all mail and configuration files encrypted, otherwise select [**No**] if you do not. If you select [**Yes**], you will be prompted for the password each time you start or configure SOHO.
7. Please enter a unique four digit System Security Code that you can remember. [**OK**].
8. Select the appropriate modem, change the COM Port as needed and click [**Done**].
9. The SOHO site is now configured. Click [**OK**].
10. The SOHO Configurator should open. Look over each tab to make sure the settings are how you want them.

If you experienced problems calling over your satellite phone, please refer to the modem configuration help files or contact UUPlus support.